



### Remote Programming – Santel “Phazr-5” UR5U-9020L

The easiest way to program this remote is by using the **CODE AUTO-SEARCH** function. Those steps are as follows:

- Press and release the **TV** button.  
(will flash under your finger when pressed)
- Press and hold the **TV** and **OK/SEL** buttons at the same time until the TV button stays lit, then release both.
- Press and hold the **CH^** (Channel Up) button until the TV turns off; LET GO of CH^ **immediately**.
- Once the TV has turned off, press and release the **TV** button (it should flash twice).
- Verify that the TV turns back on using the **POWER** button.

### STB PROGRAMMING:

- Press and hold the **CBL** and **OK/SEL** buttons until the CBL button stays lit, then release both.
- Enter the 3-digit code corresponding to your STB model.
  - AMINO KAMAI → **221**
  - AMINO A140 → **262**
  - I.S. 5112 / 5041 → **002** (Default from factory)
- Press and release the **CBL** button.
- Verify functionality.

### QUICK-ACCESS TV Programming Numbers:

- Press and release the **TV** button.
- Press and hold the **TV** button for 5 seconds.  
(should flash once then stay lit)
- Continue holding the **TV** button, press the **number** button corresponding to the button that matches your TV brand below. TV button will flash after the number is pressed.
- Let go of the **TV** button, it should flash twice after released.
- Verify power/volume.

1 – SONY	2 – SAMSUNG
3 – LG	4 – TOSHIBA
5 – PANASONIC	6 – PHILIPS
7 – HITACHI	8 – SHARP
9 – VIZIO	0 – SANYO

**\*NOTE\*** This remote does not have a “Master Power” option. Put the remote in TV mode, and it will control all Power, Volume, Channel, Guide and other STB functions just fine.